



Starfix® ferrules, crimping tools and applicators

■ Correspondance table

Cross section (mm ²)			
Ferrule	Single ferrule	Large capacity ferrule - refills	Starfix applicator
0-5	0376 61	0376 41	0376 47
0-75	0376 62	0376 42	0376 47
1-0	0376 63	0376 43	0376 47
1-5	0376 64	0376 44	0376 47
2-5	0376 66	0376 45	0376 47


■ Dimensions (mm)

Single ferrules



Cat. Nos.	Cross section (mm ²)	A	B	C	D
0376 50	0-25	8	14-5	1-1	3
0376 60	0-34	8	14-5	1-1	3
0376 61 0376 41	0-5	8	14-5	1-5	3-4
0376 62 0376 42	0-75	8	14-5	1-5	3-4
0376 63 0376 43	1-0	8	14-5	1-7	3-6
0376 64 0376 44	1-5	8	14-5	2	4-1
0376 66 0376 45	2-5	8	14-5	2-6	4-8
0376 67	4	12	21	3-2	5-7
0376 68	6	12	23	3-9	7-2
0376 69	10	12	21	4-9	8-1
0376 70	16	18	29	6-3	9-8
0376 71	25	18	31	7-9	12

Double ferrules



Cat. Nos.	Cross section (mm ²)	A	B	C	D	E
0376 87	2 x 0-75	8	15	2-1	6	3-3
0376 88	2 x 1-0	8	15	2-35	6	4
0376 89	2 x 1-5	8	16	2-6	7-2	4-2
0376 90	2 x 2-5	10	18-5	3-3	8-4	4-8

■ Starfix crimping tool usage example



1 Fit the applicator

2 Adjust

The handle gives an excellent grip



3 Insert the cable

4 Crimp