

GRÄSSLIN



DIN RAIL TIME SWITCH GRASSLIN Talento Easy C1

36100021

Digital time switch DIN, 1 CH, Astro/daily/weekly, 50 mem locations. Min switching time of 1 min or 1 sec (cycle, pulse). Geo database for 45 countries and 280 cities. Trigger modes for sunrise/sunset or dawn/dusk. Summer-winter time changeover is automatic, on a specific date or can also be deactivated.

12/24 h setting. Manual/autoc mode, fixed ON/OFF, override. Battery reserve for up to 6 years. Can be sealed and also PIN-protected against unwanted access.

SPECIFICATIONS

Operating voltage	230V AC
Frequency	50/60Hz
Width	2 modules
Type of installation	DIN-rail
Type of contact	NO contact
Power reserve	6 years
Program setting	Daily/weekly/astro
Number of channels	1 channel
Memory locations	50
Switching capacity at 250V AC, cos phi = 1	16A
Switching capacity at 250V AC, cos phi 0.6	10A
Shortest switching time	1 min/1s (pulse)
Time accuracy at 20°C	Typically ± 0.5 s/day (quartz)
Standby output	6VA
Protection rating	IP 20
Protection class	II
Ambient temperature	-10°C ~ +55°C